

PDS-4K Audio and DisplayPort 1.2 input card



- Adds Audio pass-through and Dante capability to the system
- Adds two more input connectors

Adds the ability for the PDS-4K to pass embedded audio from HDMI/DisplayPort/SDI input to Program outputs and embed/disembed to Dante network audio.

Adds two DisplayPort 1.2 input connectors.

PDS-4K includes license from Audinate Pty Ltd under US Patents 7747725, 8005939, 7978696, 8171152, European Patent 2255541, Chinese Patent ZL200780026677.0 and other patents pending or issued, see www.audinate.com/patents

TECHNISCHE SPECIFICATIES**PDS-4K AUDIO AND DISPLAYPORT 1.2 INPUT CARD**

Connectoren	2x DisplayPort 1.2 Inputs 2x RJ-45 (Dante)
Resolutie	3840x2400p @60
Kleurdiepte	10-bit
Kleursampling	4:4:4
HDCP	1.x
Signaalcapaciteit	660 MHz
Audiokanalen	2 per input or output
Audiosamplefrequentie	48 Khz
Audiobitdiepte	16bit or 24 bit
Audioformaat	PCM
AES 67 support	Yes
Number of Dante channels	64 inputs x 64 outputs (2 channels per input or output)
Kenmerken	Outputs selectable between specific input, Dante Audio, or Audio follows video PGM audio return to Dante All inputs transmit to Dante

Last updated: 16 Jun 2022

Technical specifications are subject to change without prior notice. Please check www.barco.com for the latest information.